




H A Y L O U

**Haylou-GT1**  
**TWS EARBUDS**  
User Manual

## Overview



## What's in the Box

Earbuds, charging case, EarTips × 2 pairs, user manual, charging cable



Please take off stickers and top up GT1 before use.

#### Basic Parameters

Operation range: 10m(with no obstacle)

Battery capacity: 43mAh(single EarBud)

Charging time: approx. 2.0hr

Battery life: approx. 3.5hr

Standby time: approx. 60hr

Input parameter: 5V = 100mA

Battery type: li-ion

Bluetooth version: 5.0

#### Charging case

Input parameter:5V = 500mA

Output parameter:5V= 150mA

Charging time: approx. 2hr

Standby time: approx. 4 months

Battery capacity: 310mAh

Battery type: li-ion

## Power-on

Method 1: take out earbuds to auto power on.

Method 2: keep touching the panel for 1.5s to power on.

Take out earbuds  
( auto power-on )

Keep touching  
the panel for 1.5s



LED glows  
solid white

## Power-off

Method 1: pop earbuds back into carry case to power off.

Method 2: keep touching the panel for 4.5s to power off ( LED glows solid red for 2s).

Pop them back into  
carry case ( power off)

Keep touching  
the panel for 4.5s



LED glows  
solid red  
for 2s

## Ignore Call

Keep touching the panel for 1s to ignore call.

Keep touching  
for 1s



## How to Charge

Put earbuds back into the case to charge, earbuds will auto power off . LED will glow solid red when charging and turn to white for 1 minute once top up



## Mono Mode

Auto connect : take out either earbud to power on. LED will then blink white slowly gradually. On cellphone, search for Haylou-GT1 and tap to connect.

Manual connect: power off either earbud and keep touching the panel for 1.5s to power on. LED will then blink white slowly gradually. On cellphone, search for Haylou-GT1 and tap to connect.


## Stereo Mode

### Auto pairing:

Take out both earbuds from the case. On cellphone, search for Haylou-GT1 and tap to connect.

If you fail to build connection, please pull earbuds back into the case and repeat the above steps.

Once connected, earbuds will auto reconnect to the last device in connectivity records whenever powering on ( Bluetooth faculty needs to be turned on ).



**Manual pairing:** manually power on two earbuds and they will auto pair with each other when LED blinks white promptly. Then LED on the right earbud will blink white slowly and now you can tap it on cellphone to connect.

## Functions



- Double touch left earbud  
Skip track backward
- Double touch right earbud  
Skip track forward
- Touch either earbud  
Resume playing/pause music  
(when standby)
- Double touch either earbud  
Answer/end incoming call
- Keeping touching either earbud for 1s  
Ignore incoming call
- Triple touch left earbud  
Activate voice assistant when standby
- Triple touch right earbud  
Activate gaming mode(ultra-low lag)

## Daily maintenance

Please do not shower with earbuds. Do not wear them in rainy day. Do not leave them in washing machine or other extreme situations. Clean them with dry cloth after use in pursuing a longer service life.

## Caveats

1. Please charge the product, in case it has not been used over two weeks.
2. Please use certificated charger.
3. Do not wear earphones for a long term to protect your hearing.
4. Do not wear earphones in any situations with potential risks as wearing them may reduce your perception to the outside world.



## **!** Factory Setting

If earphones do not function well, please refer the following steps to reset factory: take earbuds out from the case. Power off the earphones then hold MFBs on both earbuds for about 15s ( LED will blink red and white three times twice). After that, put them back to the case. Delete connectivity record on cellphone before processing another pairing (All connectivity records relating to the earbuds will all be removed).

## **!** Audio only outputs from single earbud

It's a rare case . Please reset the earphones, remove connectivity record on your cellphone and re-connect the earphones to your cellphone.

## **!** Other problems in charging

LED glows solid white for 1 minute when earbuds are topped up.

Carry case will not charge earbuds, if its battery drains. LEDs on carry case will turn off once the case is topped up. If you charge it once again, LEDs will not give any notice, which does not mean the case is not charged.

## Tips

1. Before using the headset, please read the manual carefully and keep it for future references.
2. The headset need to be fully charged prior to first-time use.
3. If the headset is left unused for over two weeks, please recharge it periodically.
4. Please use the chargers made by qualified manufacturer.
5. If the headset cannot be found by your phone, please check whether it is in pairing mode; if left unconnected for a long while, the headset will exit pairing mode, please re-enter the mode; if a procedure error of your phone occurs, reboot it; if a procedure error of the headset occurs, reboot or reset it.

**Address:** Suite 1303, 1305 and 1306, 13/F, Project Phrase 2 of Gaosheng Tech Tower, Gaosheng Tech Park, No.5 Longxi Road, Zhouxi Community, Nancheng District, Dongguan City, Guangdong, China.

**Manufacturer:** Dongguan Liesheng Electronic Co., Ltd.

**Web:** [www.haylou.com](http://www.haylou.com)

**Made In China**

## Hazardous substances and their contents in the item



Part Name	Hazardous Substances									
	Pb	Hg	Cd	Cr (VI)	PBB	PBDE	DIBP	DEHP	DBP	BBP
Main body	X	O	O	O	O	O	O	O	O	O
Battery	O	O	O	O	O	O	O	O	O	O
Ear tips	O	O	O	O	O	O	O	O	O	O
Accessories	O	O	O	O	O	O	O	O	O	O
Charging cable	X	O	O	O	O	O	O	O	O	O

This form is made by SJ/T 11364 regulation.

O: means that hazardous substance content in the homogeneous materials of this part is within the limits of (EU) 2015/863 regulation .

X: means that hazardous substance content in ,at least, one certain homogeneous material of this part is beyond the limits of (EU) 2015/863 regulation ,but there is no mature alternative in the industry at present, it still conforms to the EU ROHS Directive in the scope of exemption.

Notes: Please arrange using time properly as your hearing may be damaged by using the device for a long time.

## Aftersales & Support

Warranty Period:

12 months after purchase

(please keep your receipt properly)

Free Service:

If any quality defects happen during the warranty period, please take the receipt and contact with your distributor for aftersales service.

Following cases or any damages/defects that are not due to quality issue are not covered in the warranty.

1. Any defects or damages caused by natural disasters, abnormal voltage or other environmental facts.
2. Any unauthorized disassembly, modification or change of parts.
3. Any damages caused by improper use of the product including soaking, corroding, falling down, squeezing or exposure to abnormal temperature or humidity.

Model Number:
Date of Purchasing:
User's Name:
User's Phone:
User's Address:
Shop's Name:
Shop's Address:
Comments:

## FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.



FCC ID: 2AMQ6-HAYLOUGT1